

TXS-106

POWER MIXER

Parameters

Input Channels:6 Mono, 2 stereo inputs
 AUX Channels:1
 Groups:-
 DSP EFF :24 kinds of DSP EFF
 Phantom power:48V
 Signal Noise Ratio:>88dB
 Total Harmonic Distortion:0.03%
 Line input:
 Gain Zone:10dB -+20dB
 MAX Output Level:22 dBu
 Input sensitivity
 MIC Input:60dB
 LINE Input:20dB
 EQUALIZER
 HIGH:12kHz/ ± 15dB
 MID:250Hz - 8kHz/ ± 15dB
 LOW:80Hz/ ± 15dB
 Frequency response:20HZ-20kHz (+3dB)
 Max output level:0dBu
 Auxiliary max output level:19dBu(1kw,THD=0.5%)
 Earphone Max output level:19dBu/150 Ω (+25dBm)
 Power supply:100 - 240V 6A 250V



Specification

- 1.6 XLR and MIC inputs ,2 stereo inputs.
- 2.3 segments EQ in each channel.
- 3.1 AUX output.
- 4.With mute function in each channel.
- 5.4 channels equipped with FBX function.
- 6.Stereo output
- 7.24 kinds of DSP effect.
- 8.48V phantom power supply.
- 9.Built-in soundcard function,it can record when connecting with PC or phone.
- 10.7 bands EQ in main output.
- 11.MP3 player with recording and bluetooth function.
- 12.2.5 inch LED dot matrix display
- 13.Power 750W*2 8Ω
- 14.With two hand-helds