

# MK-8000

## MK-8000系列娱乐话筒 MK-8000 SERIES ENTERTAINMENT MICROPHONE



MK-8000是一款U段无线话筒，数字导频，具有数字ID身份识别功能，杜绝干扰和窜频现象，内置强大的音频处理器，相位补偿，失真修正、动态补偿、动态扩展等功能，广泛用于KTV、私人会所等娱乐场所。

MK-800 is a u-segment design wireless microphone, digital pilot, with digital ID identification function, eliminate interference and frequency channeling phenomenon; Built-in powerful audio processor, phase compensation, distortion correction, dynamic compensation, dynamic expansion, etc, widely used for KTV, private clubs and other entertainment venues.

### SPECIFICATIONS

	型号MODEL	MK-8000
接收机 RECEIVER	频率范围FREQUENCY RESPONSE	UHF640-690MHz
	接收方式 RECEIVER TYPE	FM
	调制方式 MODULATION MODE	PLL 锁相环综合控制
	频道间隔CHANNEL SPACING	250KHz
	频点数目FREQUENCY POINTS	200CH
	内容显示 CONTENTS DISPLAY	RF/AF/频率/电池/静音/通道 RF/AF/FREQUENCY/BATTERY/MUTE/CHANNEL
	射频稳定度 RF STABILITY	± 0.0005%
	最大偏移度MAX.FREQUENCY OFFSET	± 35KHz音响压缩扩展处理具有自动音量控制 AUDIO COMPRESSION EXTENSION PROCESSING WITH AUTOMATIC VOLUME CONTROL
	信噪比S/N RATIO	< 105dB
	失真度DISTORTION	> 0.5%
	静音控制 MUTE CONTROL	多重静音控制/数字ID导频 MULTIPLE MUTE CONTROLS / DIGITAL ID PILOT
	频率响应FREQUENCY RESPONSE	30Hz-18KHz(± 3dB)
	灵敏度SENSITIVITY	输入INPUT 10-15dBV时 S/N: > 70dB
	谐波抑制比HARMONIC SUPPRESSION	> 80dB
	副谐波SUBHARMONIC	> 50dBc
接收距离 RECEIVING DISTANCE	可视距离50米左右 VISUAL DISTANCE 50M	
天线搭配 ANTENNA MATCH	高、中、低(可选)附加天线另计距离HIGH/MEDIUM/LOW(OPTIONAL), ADDITIONAL ANTENNA (DISTANCE CALCULATED SEPARATELY)	
天线接口 ANTENNA INTERFACE	BNC/50Ω	
发射机 TRANSMITTER	频率范围 FREQUENCY RESPONSE	UHF640-690MHz
	发射功率 TRANSMITTING POWER	10-30mW
	音头搭配 CAPSULE	动圈式 DYNAMIC
	话筒搭配 MICROPHONE	手持/领夹/头戴 HANDHELD / HEADWORN / CLIP MICROPHONE
	电源供应 POWER REQUIREMENTS	DC 12V 1A